



# MINI DIRECT FEED 300W SURFACE TRANSFORMER

The Mini answers the question, how small can it be? At 1.4 inches deep and 5.25 inches in diameter, it is the smallest 300 watt surface Monorail transformer in the industry. It installs similarly to our existing family of 300 watt transformers and practically disappears on the Monorail system.



## THE MINI

Truly minimalist design and the industry's smallest 300 watt surface transformer. Constructed of die-cast aluminum. Mounts to a standard 4" ceiling junction box with round plaster ring (provided by electrician). To be used with special standoff specifically designed for this transformer.

<b>MINI</b>	<b>LED</b>
<b>MODEL</b>	<b>TRANSDIRMNE300</b>
<b>FINISH</b>	<b>BZ</b> bronze <b>SC</b> satin nickel



<b>DIRECT FEED STANDOFF FOR MINI</b>	
<b>MODEL</b>	<b>HANGERDIRM</b>
<b>FINISH</b>	<b>BZ</b> bronze <b>SC</b> satin nickel

TRANSFORMER	WATTAGE & TYPE	MODEL NUMBER	INPUT	OUTPUT	COMPATIBLE DIMMER*	COMPATIBLE STANDOFF
 <b>LED</b>	12 volt / 300W Electronic Mini Direct Feed Single-Feed	TRANSDIRMNE300 (BZ, SC)	1x120VAC/2.5A	1x300W	Electronic Low-voltage v Dimmer 600W	Standoff for Mini Direct Feed

**LED** Indicates which transformers are compatible with LED fixtures

\*As a general rule when using LED fixtures we do not recommend using greater than 70% of specified maximum wattage on the transformer due to inrush current. For assistance, please contact our technical support department.

